

## **IrDA<sup>®</sup> Compliant Protocol Processor**

### **ACT-IR8200D**

- A complete IrDA<sup>®</sup> Protocol stack in a single chip.
- No any driver is needed.
- Includes IrPHY<sup>™</sup> encoding/decoding and interfaces directly to Infrared transceivers for data rate up to 115.2 kbps. Only an external Infrared transceiver is needed to complete an IrDA<sup>®</sup> compliant infrared communication subsystem.
- Supports mandatory IrDA<sup>®</sup> layer: IrPHY<sup>™</sup>, IrLAP<sup>™</sup>, IrLMP<sup>™</sup> and IAS.
- Supports upper layers TinyTP, IrCOMM<sup>™</sup>, IrLPT<sup>™</sup>, and OBEX<sup>™</sup> transport.
- Supports host baud rate from 1.2 kbps to 115.2 kbps, which is changed by PC utility or 8 pins on chip. IrDA<sup>®</sup> baud rate from 9.6 kbps to 115.2 kbps, which is flexible, setting by IrDA<sup>®</sup> devices.
- Supports both IrDA<sup>®</sup> Primary and Secondary mode
- IR frame and Host buffer are 2048 bytes separately.
- Low supply voltage, 3.0 V to 3.6 V.
- Current consumption: 20mA standby, 30mA active.
- Small low profile plastic 52-pin QFP package.
- Available in programmed and tested chips, assembled & tested boards, or fully packaged devices.
- A ready-made IrDA<sup>®</sup>-compatible evaluation dongle ACT-IR100SD is available. It is strongly recommended to test ACT-IR100SD before purchasing ACT-IR8200D chip.

All trademarks, company and product names belong to the trademarks and names of the respective organizations & companies.

